

8Bit-Museum.de

ROM, PROM, EPROM memory comparison table for the "Retro Chip Tester Professional"

Identifier	Company	Test setting	Pro Rev.1+	Organization	Size	TS/OC/AP	Pins	Type	Remark
EPROMs (and compatible (P)ROMs)									
1702A	Intel	1702	adapter	256 x 8	2048		24	EPROM	requires adapter, U = -9V
1302A	Intel	1702	adapter	256 x 8	2048		24	ROM	requires adapter, U = -9V
1602A	Intel	1702	adapter	256 x 8	2048		24	PROM	requires adapter, U = -9V
Am1702A	AMD	1702	adapter	256 x 8	2048		24	EPROM	requires adapter, U = -9V
MM1702A	National	1702	adapter	256 x 8	2048		24	EPROM	requires adapter, U = -9V
1702A	Signetics	1702	adapter	256 x 8	2048		24	EPROM	requires adapter, U = -9V
U501	(DDR)	1702	adapter	256 x 8	2048		24	ROM	requires adapter, U = -9V
U551	(DDR)	1702	adapter	256 x 8	2048		24	PROM	requires adapter, U = -9V
U552	(DDR)	1702	adapter	256 x 8	2048		24	EPROM	requires adapter, U = -9V
K505PP1	(UdSSR)	1702	adapter	256 x 8	2048		24	EPROM	requires adapter, U = -9V, untested
CDP18U42CD	RCA	745271/470	adapter	256 x 8	2048	TS	24	EPROM	12=Vcc, 22=Vsat, 23=Vdd, 24=Vss, single 5V read, untested
2704		2704	X	512 x 8	4096		24	EPROM	24=Vcc, 21=Vbb, 19=Vdd, 12/22=Vss, untested
2704	Intel	2704	X	512 x 8	4096		24	EPROM	24=Vcc, 21=Vbb, 19=Vdd, 12/22=Vss, untested
CDP1832	RCA	2704	X	512 x 8	4096		24	EPROM	24=Vcc, 21=nc, 19=nc, 12=Vss, 5V only, untested
MM4204	National	2704	adapter	512 x 8	4096	TS	24	EPROM	U = -12V, 5V, use 2704 settings with adapter
MM5204	National	2704	adapter	512 x 8	4096	TS	24	EPROM	U = -12V, 5V, use 2704 settings with adapter
2708	Intel	2708	X	1k x 8	8192		24	EPROM	24=Vcc, 21=Vbb, 19=Vdd, 12=Vss
F2708	Fairchild	2708	X	1k x 8	8192		24	EPROM	24=Vcc, 21=Vbb, 19=Vdd, 12=Vss
F2708	Fairchild	2708	X	1k x 8	8192		24	EPROM	24=Vcc, 21=Vbb, 19=Vdd, 12=Vss
MB8518	Fujitsu	2708	X	1k x 8	8192		24	EPROM	24=Vcc, 21=Vbb, 19=Vdd, 12=Vss
SFF71708	Mostek	2708	X	1k x 8	8192		24	EPROM	24=Vcc, 21=Vbb, 19=Vdd, 12=Vss
MCM2708	Motorola	2708	X	1k x 8	8192		24	EPROM	24=Vcc, 21=Vbb, 19=Vdd, 12=Vss
MCM68708	Motorola	2708	X	1k x 8	8192		24	EPROM	24=Vcc, 21=Vbb, 19=Vdd, 12=Vss
MM2708	National	2708	X	1k x 8	8192		24	EPROM	24=Vcc, 21=Vbb, 19=Vdd, 12=Vss
NTE2708	NTE	2708	X	1k x 8	8192		24	EPROM	24=Vcc, 21=Vbb, 19=Vdd, 12=Vss
MSM2708	Oki	2708	X	1k x 8	8192		24	EPROM	24=Vcc, 21=Vbb, 19=Vdd, 12=Vss
TMS2708	Texas Instruments	2708	X	1k x 8	8192		24	EPROM	24=Vcc, 21=Vbb, 19=Vdd, 12=Vss
MSM3758	Oki	2708	X	1k x 8	8192		24	EPROM	24=Vcc, 21=Vbb, 19=Vdd, 12=Vss
CDP1834	RCA	2708	X	1k x 8	8192		24	EPROM	24=Vcc, 21=nc, 19=nc, 12=Vss, 5V only, untested
U505	(DDR)	2708	X	1k x 8	8192		24	ROM	5V only
U555	(DDR)	2708	X	1k x 8	8192		24	EPROM	24=Vcc, 21=Vbb, 19=Vdd, 12=Vss
K573P01	(UdSSR)	2708	X	1k x 8	8192		24	EPROM	24=Vcc, 21=Vbb, 19=Vdd, 12=Vss
K573RF1	(UdSSR)	2708	X	1k x 8	8192		24	EPROM	24=Vcc, 21=Vbb, 19=Vdd, 12=Vss
2716	Intel	2716	X	2k x 8	16384		24	EPROM	
Am2716	AMD	2716	X	2k x 8	16384		24	EPROM	
Am4716	AMD	2716	X	2k x 8	16384		24	EPROM	
NMC27C16	Fairchild	2716	X	2k x 8	16384		24	EPROM	
MBM2716	Fujitsu	2716	X	2k x 8	16384		24	EPROM	
HN462716	Hitachi	2716	X	2k x 8	16384		24	EPROM	
MMN2716	Microelectronica	2716	X	2k x 8	16384		24	EPROM	
MSL2716	Mitsubishi	2716	X	2k x 8	16384		24	EPROM	
MCM2716	Motorola	2716	X	2k x 8	16384		24	EPROM	
27C16	National	2716	X	2k x 8	16384		24	EPROM	
MM2716	National	2716	X	2k x 8	16384		24	EPROM	
uPD2716	NEC	2716	X	2k x 8	16384		24	EPROM	
NTE2716	NTE	2716	X	2k x 8	16384		24	EPROM	
MSM2716	Oki	2716	X	2k x 8	16384		24	EPROM	
M2716	SGS	2716	X	2k x 8	16384		24	EPROM	
M2716	ST Microelectronics	2716	X	2k x 8	16384		24	EPROM	
TMM323	Toshiba	2716	X	2k x 8	16384		24	EPROM	
TMS2516	Texas Instruments	2716	X	2k x 8	16384		24	EPROM	
ET2716	Thomson	2716	X	2k x 8	16384		24	EPROM	
U556	(DDR)	2716	X	2k x 8	16384		24	EPROM	
K573RF2	(UdSSR)	2716	X	2k x 8	16384		24	EPROM	
TMS2716	Motorola	TMS2716	X	2k x 8	16384		24	EPROM	12=Vss, 19=Vdd, 21=Vbb, 24=Vcc
TMS2716	Texas Instruments	TMS2716	X	2k x 8	16384		24	EPROM	12=Vss, 19=Vdd, 21=Vbb, 24=Vcc
2732	Intel	2732	X	4k x 8	32768		24	EPROM	
Am2732	AMD	2732	X	4k x 8	32768		24	EPROM	
F2732	Fairchild	2732	X	4k x 8	32768		24	EPROM	
NMC27C32	Fairchild	2732	X	4k x 8	32768		24	EPROM	
MB8532	Fujitsu	2732	X	4k x 8	32768		24	EPROM	
MBM2732	Fujitsu	2732	X	4k x 8	32768		24	EPROM	
CDM5332	GE	2732	X	4k x 8	32768		24	ROM	compatible to 2732
Ro9333	GI	2732	X	4k x 8	32768		24	ROM	compatible to 2732, readable when 18/20=LOW
Ro9433	GI	2732	X	4k x 8	32768		24	ROM	compatible to 2732, readable when 18/20=LOW
HN462732	Hitachi	2732	X	4k x 8	32768		24	EPROM	
2732A	Intel	2732	X	4k x 8	32768		24	EPROM	
MSL2732	Mitsubishi	2732	X	4k x 8	32768		24	EPROM	
NMC27C32	National	2732	X	4k x 8	32768		24	EPROM	
uPD2732	NEC	2732	X	4k x 8	32768		24	EPROM	
M2732	ST Microelectronics	2732	X	4k x 8	32768		24	EPROM	
TMM2732	Toshiba	2732	X	4k x 8	32768		24	EPROM	
TMS2732	Texas Instruments	2732	X	4k x 8	32768		24	EPROM	
WS57C43	WSI	2732	X	4k x 8	32768		24	PROM	compatible to 2732, readable when 18=HIGH, 20=LOW
U2732	(DDR)	2732	X	4k x 8	32768		24	EPROM	
2333		2732	X	4k x 8	32768		24	ROM	compatible to 2732, readable when 18/20=LOW
2764	Intel	2764	X	8k x 8	65536		28	EPROM	
Am2764A	AMD	2764	X	8k x 8	65536		28	PROM	
MBM2764	Fujitsu	2764	X	8k x 8	65536		28	EPROM	
MBM27C64	Fujitsu	2764	X	8k x 8	65536		28	EPROM	
HN482764	Hitachi	2764	X	8k x 8	65536		28	ROM	
2764A	Intel	2764	X	8k x 8	65536		28	EPROM	
MK37000	Mostek	2764	X	8k x 8	65536		28	ROM	1/26/27=nc
NMC27C64	National	2764	X	8k x 8	65536		28	EPROM	
M2764	SGS-Thomson	2764	X	8k x 8	65536		28	EPROM	
M2764A	ST Microelectronics	2764	X	8k x 8	65536		28	EPROM	
U2764	(DDR)	2764	X	8k x 8	65536		28	EPROM	
TMS2564	Texas Instruments	TMS2564	X	8k x 8	65536		28	EPROM	
27128	Intel	27128	X	16k x 8	131072		28	EPROM	
Am27128A	AMD	27128	X	16k x 8	131072		28	PROM	
MBM27128	Fujitsu	27128	X	16k x 8	131072		28	EPROM	
HN4827128	Hitachi	27128	X	16k x 8	131072		28	EPROM	
NM27C128	National	27128	X	16k x 8	131072		28	EPROM	
UPD27128	NEC	27128	X	16k x 8	131072		28	EPROM	
M27128A	ST Microelectronics	27128	X	16k x 8	131072		28	EPROM	
TMM24128	Toshiba	27128	X	16k x 8	131072		28	PROM	untested
27256	Intel	27256	X	32k x 8	262144		28	EPROM	
6212424	AMD	27256	X	32k x 8	262144		28	EPROM	

Identifier	Company	Test setting	Pro Rev.1+	Organization	Size	TS/OC/AP	Pins	Type	Remark
Am27256	AMD	27256	X	32k x 8	262144		28	PROM	
MB27C256	Fujitsu	27256	X	32k x 8	262144		28	EPROM	
27256	GI	27256	X	32k x 8	262144		28	EPROM	
NM27C256	National	27256	X	32k x 8	262144		28	EPROM	
NMC27C256	National	27256	X	32k x 8	262144		28	EPROM	
TMS27C256	Texas Instruments	27256	X	32k x 8	262144		28	EPROM	
TC57H256	Toshiba	27256	X	32k x 8	262144		28	EPROM	
27512	Intel	27512	X	64k x 8	524288		28	EPROM	
A276308	Amic	27512	X	64k x 8	524288		28	EPROM	
M27512	ST Microelectronics	27512	X	64k x 8	524288		28	EPROM	
M27C512	ST Microelectronics	27512	X	64k x 8	524288		28	EPROM	
TMS27C512	Texas Instruments	27512	X	64k x 8	524288		28	EPROM	
TC57C512	Toshiba	27512	X	64k x 8	524288		28	EPROM	
27010		271001	X	128k x 8	1 MBit		32	EPROM	
271001		271001	X	128k x 8	1 MBit		32	EPROM	
Am27C1001	AMD	271001	X	128k x 8	1 MBit		32	EPROM	
AT27C010	Atmel	271001	X	128k x 8	1 MBit		32	EPROM	
MX27C1000	Macronix	271001	X	128k x 8	1 MBit		32	EPROM	
KM23C1010	Samsung	271001	X	128k x 8	1 MBit		32	ROM	
LH530800A	Sharp	271001	X	128k x 8	1 MBit		32	ROM	
M27C1001	ST Microelectronics	271001	X	128k x 8	1 MBit		32	EPROM	
TMS27C010	Texas Instruments	271001	X	128k x 8	1 MBit		32	EPROM	
TC531001	Toshiba	271001	X	128k x 8	1 MBit		32	ROM	
TC571000	Toshiba	271001	X	128k x 8	1 MBit		32	EPROM	
HN27C301	Hitachi	27301	(X)	128k x 8	1 MBit		32	EPROM	untested
TC571001	Toshiba	27301	(X)	128k x 8	1 MBit		32	EPROM	untested
27020		272001	X	256k x 8	2 MBit		32	EPROM	
27C020		272001	X	256k x 8	2 MBit		32	EPROM	
272001		272001	X	256k x 8	2 MBit		32	EPROM	
27C2001		272001	X	256k x 8	2 MBit		32	EPROM	
A278308	Amic	272001	X	256k x 8	2 MBit		32	EPROM	
272001	ST Microelectronics	272001	X	256k x 8	2 MBit		32	EPROM	
MBM27C4000	Fujitsu	custom	external	512k x 8	4 MBit		32	EPROM	not compatible with standard 274000, pin 2 and 24 swapped, untested
27040		274001	X	512k x 8	4 MBit		32	EPROM	
274001		274001	X	512k x 8	4 MBit		32	EPROM	
Am27C040	AMD	274001	X	512k x 8	4 MBit		32	EPROM	
MX27C4000	Macronix	274001	X	512k x 8	4 MBit		32	EPROM	
274001	ST Microelectronics	274001	X	512k x 8	4 MBit		32	EPROM	
TMS27C040	Texas Instruments	274001	X	512k x 8	4 MBit		32	EPROM	
27C080		custom	external	1024k x 8	8 MBit		32	EPROM	external definition available
AT27C080	Atmel	custom	external	1024k x 8	8 MBit		32	EPROM	external definition available
M27C801	ST Microelectronics	custom	external	1024k x 8	8 MBit		32	EPROM	external definition available
(P)ROMs (and compatible EPROMs)									
2513		2704	adapter	64 x 8 x 5	2560	TS	24	ChrROM	with -5V/-12V, use 2704 settings with adapter, untested
RO-3-2513	GI	2704	adapter	64 x 8 x 5	2560	TS	24	ChrROM	5V only, use 2704 settings with adapter, untested
RO-3-2513	GI	RO-3-2513	X	64 x 8 x 5	2560	TS	24	ChrROM	5V only
MCM6670	Motorola	6670	X	128 x 7 x 5	4480	TS	18	ChrROM	row 0 is always read (=0, 128x8x5)
MCM6674	Motorola	6670	X	128 x 7 x 5	4480	TS	18	ChrROM	row 0 is always read (=0, 128x8x5)
SCM37530	Motorola	6670	X	128 x 7 x 5	4480	TS	18	ChrROM	row 0 is always read (=0, 128x8x5), DO-D4 reversed(!)
2308		2308	X	1k x 8	8192		24	ROM	18/20=LOW or 18=HIGH, 20=LOW
Am9208	AMD	2308	X	1k x 8	8192		24	ROM	18/20=LOW or 18/20=HIGH, 19=Vdd, 21=NC
F3508	Fairchild	2308	X	1k x 8	8192		24	ROM	18/20=LOW or 18=HIGH, 20=LOW, single 5V only
2308	Intel	2308	X	1k x 8	8192		24	ROM	18/20=LOW or 18=HIGH, 20=LOW
2608	Intel	2308	X	1k x 8	8192		24	ROM	18/20=LOW, single 5V only, Pin 18 must be LOW (Vss)
MK30000	Mostek	2308	X	1k x 8	8192		24	ROM	18/20=LOW, single 5V only, Pin 18 must be LOW (Vss)
2607	Signetics	2308	X	1k x 8	8192		24	ROM	18/20=LOW or 18=HIGH, 20=LOW, single 5V only
TMS4700	Texas Instruments	2308	X	1k x 8	8192		24	ROM	18/20=LOW or 18=HIGH, 20=LOW
Am8316A	AMD	2316A	X	2k x 8	16384	TS	24	ROM	15/14/13=LOW, untested
Am9217	AMD	2316A	X	2k x 8	16384	TS	24	ROM	15/14/13=LOW, untested
56831A	AMI	2316A	X	2k x 8	16384	TS	24	ROM	15/14/13=LOW, untested
RO-3-8316(AB)	GI	2316A	X	2k x 8	16384	TS	24	ROM	15/14/13=LOW, untested
2316A	Intel	2316A	X	2k x 8	16384	TS	24	ROM	15/14/13=LOW
4316A	Intel	2316A	X	2k x 8	16384	TS	24	ROM	15/14/13=LOW, untested
8316A	Intel	2316A	X	2k x 8	16384	TS	24	ROM	15/14/13=LOW, untested
MM2316A	National	2316A	X	2k x 8	16384	TS	24	ROM	15/14/13=LOW
MK31000	Mostek	2316A	X	2k x 8	16384	TS	24	ROM	15/14/13=LOW, untested
MCM68A316	Motorola	2316A	X	2k x 8	16384	TS	24	ROM	15/14/13=LOW, untested
uPD2316A	NEC	2316A	X	2k x 8	16384	TS	24	ROM	15/14/13=LOW
SY2316A	Synertec	2316A	X	2k x 8	16384	TS	24	ROM	15/14/13=LOW
TMM331AP	Toshiba	2316A	X	2k x 8	16384	TS	24	ROM	15/14/13=LOW
2316B		2316B	X	2k x 8	16384		24	ROM	18/20=LOW, 21=HIGH or 20/21=LOW, 18=HIGH
Am9218	AMD	2316B	X	2k x 8	16384		24	ROM	18/20=LOW, 21=HIGH or 20/21=LOW, 18=HIGH
HM7616	Harris	2316B	X	2k x 8	16384	TS	24	PROM	18/21=NC, 20=LOW, untested
2316E	Intel	2316B	X	2k x 8	16384		24	ROM	18/20=LOW, 21=HIGH or 20/21=LOW, 18=HIGH
2616	Intel	2316B	X	2k x 8	16384		24	ROM	18/20=LOW, 21=HIGH or 20/21=LOW, 18=HIGH
IM6316	Intersil	2316B	X	2k x 8	16384		24	ROM	18/20=LOW, 21=HIGH or 20/21=LOW, 18=HIGH, untested
RO-3-9316(ABC)	GI	2316B	X	2k x 8	16384		24	ROM	18/20=LOW, 21=HIGH or 20/21=LOW, 18=HIGH
MMN2616	Microelectronica	2316B	X	2k x 8	16384		24	ROM	18/20=LOW, 21=HIGH or 20/21=LOW, 18=HIGH
2316	Mostek	2316B	X	2k x 8	16384		24	ROM	18/20=LOW, 21=HIGH or 20/21=LOW, 18=HIGH
MK34000	Mostek	2316B	X	2k x 8	16384		24	ROM	18/20=LOW, 21=HIGH or 20/21=LOW, 18=HIGH
MCM68316E	Motorola	2316B	X	2k x 8	16384		24	ROM	18/20=LOW, 21=HIGH or 20/21=LOW, 18=HIGH
MCM68A316E	Motorola	2316B	X	2k x 8	16384		24	ROM	18/20=LOW, 21=HIGH or 20/21=LOW, 18=HIGH
MM52116	National	2316B	X	2k x 8	16384		24	ROM	18/20=LOW, 21=HIGH or 20/21=LOW, 18=HIGH
uPD2316E	NEC	2316B	X	2k x 8	16384		24	ROM	18/20=LOW, 21=HIGH or 20/21=LOW, 18=HIGH
M2316E	SGS-Thomson	2316B	X	2k x 8	16384		24	ROM	18/20=LOW, 21=HIGH or 20/21=LOW, 18=HIGH
2616	Signetics	2316B	X	2k x 8	16384		24	ROM	18/20=LOW, 21=HIGH or 20/21=LOW, 18=HIGH
SY2316B	Synertec	2316B	X	2k x 8	16384		24	ROM	18/20=LOW, 21=HIGH or 20/21=LOW, 18=HIGH
SBP8316	Texas Instruments	2316B	X	2k x 8	16384		24	ROM	18/20=LOW, 21=HIGH or 20/21=LOW, 18=HIGH, ICS, untested
SBP8918	Texas Instruments	2316B	X	2k x 8	16384		24	ROM	18/20=LOW, 21=HIGH or 20/21=LOW, 18=HIGH, untested
TMM334P	Toshiba	2316B	X	2k x 8	16384		24	ROM	18/20=LOW, 21=HIGH or 20/21=LOW, 18=HIGH
2332		2332	X	4k x 8	32768		24	ROM	20=LOW, 21=HIGH or 20/21=LOW
CDM5333	GE	2332	X	4k x 8	32768		24	ROM	20=LOW, 21=HIGH or 20/21=LOW
Ro-3-9332(ABC)	GI	2332	X	4k x 8	32768		24	ROM	20=LOW, 21=HIGH or 20/21=LOW
Ro9432(BCD)	GI	2332	X	4k x 8	32768		24	ROM	20=LOW, 21=HIGH or 20/21=LOW
HN462532	Hitachi	2332	X	4k x 8	32768		24	EPROM	20=LOW, 21=HIGH, compatible 2532
MK32000	Mostek	2332	X	4k x 8	32768		24	ROM	20=LOW, 21=HIGH or 20/21=LOW
MPS2332	MOS	2332	X	4k x 8	32768		24	ROM	20=LOW, 21=HIGH or 20/21=LOW
MPS6332	MOS	2332	X	4k x 8	32768		24	ROM	20=LOW, 21=HIGH or 20/21=LOW
MCM2532	Motorola	2332	X	4k x 8	32768		24	EPROM	20=LOW, 21=HIGH, compatible 2532
MCM68A332	Motorola	2332	X	4k x 8	32768		24	ROM	20=LOW, 21=HIGH or 20/21=LOW
MCM68732-0	Motorola	2332	X	4k x 8	32768		24	ROM	20/21=LOW, untested
MCM68732-1	Motorola	2332	X	4k x 8	32768		24	ROM	20=LOW, 21=HIGH, untested
TMS2532	Texas Instruments	2332	X	4k x 8	32768		24	EPROM	20=LOW, 21=HIGH
TMS4732	Texas Instruments	2332	X	4k x 8	32768		24	ROM	ROM, 20=LOW, 21=HIGH or 20/21=LOW
TMM333P	Toshiba	2332	X	4k x 8	32768		24	ROM	20=LOW, 21=HIGH or 20/21=LOW

Identifier	Company	Test setting	Pro Rev.1+	Organization	Size	TS/OC/AP	Pins	Type	Remark
2364		2364(24)	X	8k x 8	65536		24	ROM	20=LOW or 20=HIGH
MPS2364	Mostek	2364(24)	X	8k x 8	65536		24	ROM	20=LOW
MK36000	Mostek	2364(24)	X	8k x 8	65536		24	ROM	20=LOW
RO-3-9364	GI	2364(24)	X	8k x 8	65536		24	ROM	20=LOW or 20=HIGH, untested
Ro9464	GI	2364(24)	X	8k x 8	65536		24	ROM	20=LOW or 20=HIGH, untested
Ro9464(BCD/ABCD)	GI	2364(24)	X	8k x 8	65536		24	ROM	20=LOW, untested
2364	MOS	2364(24)	X	8k x 8	65536		24	ROM	20=LOW or 20=HIGH, untested
MCM68364	Motorola	2364(24)	X	8k x 8	65536		24	ROM	20=LOW, untested
MCM68366	Motorola	2364(24)	X	8k x 8	65536		24	ROM	20=LOW, untested
MCM68764	Motorola	2364(24)	X	8k x 8	65536		24	EPROM	20=LOW, untested
MCM68766	Motorola	2364(24)	X	8k x 8	65536		24	EPROM	20=LOW
MM52164	National	2364(24)	X	8k x 8	65536		24	ROM	20=LOW, untested
uPD2364	NEC	2364(24)	X	8k x 8	65536		24	ROM	20=LOW
2664A	Signetics	2364(24)	X	8k x 8	65536		24	ROM	20=LOW, untested
SY2364	Synertec	2364(24)	X	8k x 8	65536		24	ROM	20=LOW, untested
TMS4764	Texas Instruments	2364(24)	X	8k x 8	65536		24	ROM	20=LOW or 20=HIGH, untested
TMM2366	Toshiba	2364(24)	X	8k x 8	65536		24	ROM	20=LOW, untested
2365		2364(28)	X	8k x 8	65536		28	ROM	20/22=LOW, 26/27=HIGH, untested
Ro9864	GI	2364(28)	X	8k x 8	65536		28	ROM	20/22=LOW, 26/27=HIGH, untested
Ro9864A	GI	2364(28)	X	8k x 8	65536		28	ROM	20/22=LOW, 26/27=HIGH, untested
Ro-3-9365	GI	2364(28)	X	8k x 8	65536		28	ROM	20/22=LOW, 26/27=NC, untested
MK37000	Mostek	2364(28)	X	8k x 8	65536		28	ROM	20/22=LOW, 26/27=NC, untested
TMM2364	Toshiba	2364(28)	X	8k x 8	65536		28	ROM	20/22=LOW, 26/27=HIGH, untested
TMM2365	Toshiba	2364(28)	X	8k x 8	65536		28	ROM	20/22=LOW, 26/27=HIGH, untested
23128		23128	X	16k x 8	131072		28	ROM	27=HIGH, 22/20=LOW or 20/22/27=LOW or 20/22=HIGH, 27=LOW
Ro92128(BCD)	GI	23128	X	16k x 8	131072		28	ROM	27=HIGH, 22/20=LOW or 20/22/27=LOW
HN613128	Hitachi	23128	X	16k x 8	131072		28	ROM	27=HIGH, 22/20=LOW or 20/22/27=LOW or 20/22=HIGH, 27=LOW
MPS23128	Mostek	23128	X	16k x 8	131072		28	ROM	27=HIGH, 22/20=LOW or 20/22/27=LOW or 20/22=HIGH, 27=LOW
uPD23128	NEC	23128	X	16k x 8	131072		28	ROM	27=HIGH, 22/20=LOW or 20/22/27=LOW or 20/22=HIGH, 27=LOW
23256		23256	X	32k x 8	262144		28	ROM	20/22=LOW or 20=LOW, 22=HIGH
MB83256	Fujitsu	23256	X	32k x 8	262144		28	ROM	20/22=LOW
Ro9256	GI	23256	X	32k x 8	262144		28	ROM	20/22=LOW
MK38000	Mostek	23256	X	32k x 8	262144		28	ROM	20/22=LOW or 20=LOW, 22=HIGH
LH53259	Sharp	23256	X	32k x 8	262144		28	ROM	20/22=LOW or 20=LOW, 22=HIGH
TCS3257	Toshiba	23256	X	32k x 8	262144		28	ROM	20/22=LOW or 20=HIGH, 22=LOW
TMM23256	Toshiba	23256	X	32k x 8	262144		28	ROM	20/22=LOW or 20=LOW, 22=HIGH
UM23256	UMC	23256	X	32k x 8	262144		28	ROM	20/22=LOW or 20=LOW, 22=HIGH
UM23256A	UMC	23256	X	32k x 8	262144		28	ROM	20/22=LOW
23512		23512	X	64k x 8	524288		28	ROM	22/20=LOW
MB83512	Fujitsu	23512	X	64k x 8	524288		28	ROM	22/20=LOW
LH53517	Sharp	23512	X	64k x 8	524288		28	ROM	22/20=LOW or 20=LOW, 22=HIGH
VT23512	VLSI Technology	23512	X	64k x 8	524288		28	ROM	22/20=LOW
231000		231000	X	128k x 8	1 Mbit		28	ROM	20=LOW
MB831000	Fujitsu	231000	X	128k x 8	1 Mbit		28	ROM	20=LOW
HN62321	Hitachi	231000	X	128k x 8	1 Mbit		28	ROM	20=LOW, untested, note: HN62321A is 32 pin
uPD23C1000A	NEC	231000	X	128k x 8	1 Mbit		28	ROM	20=LOW
uPD231010A	NEC	231000	X	128k x 8	1 Mbit		28	ROM	20=LOW
uPD531000B	NEC	231000	X	128k x 8	1 Mbit		28	ROM	20=LOW (20=HIGH not supported)
MN231001	Panasonic	231000	X	128k x 8	1 Mbit		28	ROM	20=LOW
LH231000B	Sharp	231000	X	128k x 8	1 Mbit		28	ROM	20=LOW
LH531000B	Sharp	231000	X	128k x 8	1 Mbit		28	ROM	20=LOW
KM23C1000	Samsung	231000	X	128k x 8	1 Mbit		28	ROM	20=LOW
TCS31000	Toshiba	231000	X	128k x 8	1 Mbit		28	ROM	20=LOW
HN62321A	Hitachi	custom	external	128k x 8	1 Mbit		32	ROM	untested, note: HN62321 is 28 pin
232000		232000	X	256k x 8	2 Mbit		32	ROM	22/24=LOW
MB832000	Fujitsu	232000	X	256k x 8	2 Mbit		32	ROM	22/24=LOW
HN62302B	Hitachi	232000	X	256k x 8	2 Mbit		32	ROM	22/24=LOW
MX23C2000	Macronix	232000	X	256k x 8	2 Mbit		32	ROM	22/24=LOW or 22=HIGH, 24=LOW or 22=LOW, 24=HIGH
uPD23C2001	NEC	232000	X	256k x 8	2 Mbit		32	ROM	22/24=LOW
234000		234000	X	512k x 8	4 Mbit		32	ROM	22/24=LOW
MB834000A	Fujitsu	234000	X	512k x 8	4 Mbit		32	ROM	22/24=LOW
HN62314B	Hitachi	234000	X	512k x 8	4 Mbit		32	ROM	22/24=LOW
HN62335B	Hitachi	234000	X	512k x 8	4 Mbit		32	ROM	22/24=LOW
HN62344B	Hitachi	234000	X	512k x 8	4 Mbit		32	ROM	22/24=LOW
MX23C4000	Macronix	234000	X	512k x 8	4 Mbit		32	ROM	22/24=LOW
TCS34000	Toshiba	234000	X	512k x 8	4 Mbit		32	ROM	22/24=LOW or 22=HIGH, 24=LOW
23C8000		custom	external	1024k x 8	8 Mbit		32	ROM	22/24=LOW, external definition available
MB838000	Fujitsu	custom	external	1024k x 8	8 Mbit		32	ROM	22/24=LOW, external definition available
MX23C8000	Macronix	custom	external	1024k x 8	8 Mbit		32	ROM	22/24=LOW, external definition available
6540	MOS	6540	X	2k x 8	16384		28	ROM	2/3/4=LOW, 17/27=HIGH, 12=Vcc/1=Vss
23168		2716	X	2k x 8	16384		24	PROM	no guarantee, compatible 2716
2333		2732	X	4k x 8	32768		24	PROM	no guarantee, =2732 (when CS1/CS2 low active)
2365		2764	X	8k x 8	65536		24	PROM	no guarantee, =2764 (when CS1/CS2/CS3/CS4 low active)
Bipolar (P)ROMs									
7488		7488/188/288	X	32 x 8	256		OC	16	ROM
74188		7488/188/288	X	32 x 8	256		OC	16	PROM
74288		7488/188/288	X	32 x 8	256		TS	16	PROM
Am27508	AMD	7488/188/288	X	32 x 8	256		OC	16	PROM
Am27509	AMD	7488/188/288	X	32 x 8	256		TS	16	PROM
Am27518	AMD	7488/188/288	X	32 x 8	256		OC	16	PROM
Am27519	AMD	7488/188/288	X	32 x 8	256		TS	16	PROM
93434	Fairchild	7488/188/288	X	32 x 8	256		OC	16	PROM
MB7051	Fujitsu	7488/188/288	X	32 x 8	256		TS	16	PROM
MB7056	Fujitsu	7488/188/288	X	32 x 8	256		OC	16	PROM
HM7602	Harris	7488/188/288	X	32 x 8	256		OC	16	PROM
HM7603	Harris	7488/188/288	X	32 x 8	256		TS	16	PROM
IM5600	Intersil	7488/188/288	X	32 x 8	256		OC	16	PROM
IM5610	Intersil	7488/188/288	X	32 x 8	256		AP	16	PROM
5330	MMI	7488/188/288	X	32 x 8	256		OC	16	PROM
5331	MMI	7488/188/288	X	32 x 8	256		TS	16	PROM
6330	MMI	7488/188/288	X	32 x 8	256		OC	16	PROM
6331	MMI	7488/188/288	X	32 x 8	256		TS	16	PROM
635080	MMI	7488/188/288	X	32 x 8	256		OC	16	PROM
635081	MMI	7488/188/288	X	32 x 8	256		TS	16	PROM
uPD400	NEC	7488/188/288	X	32 x 8	256		OC	16	PROM
uPD410	NEC	7488/188/288	X	32 x 8	256		TS	16	PROM
82523	Signetics	7488/188/288	X	32 x 8	256		OC	16	PROM
825123	Signetics	7488/188/288	X	32 x 8	256		TS	16	PROM
18530	Texas Instruments	7488/188/288	X	32 x 8	256		TS	16	PROM
185A30	Texas Instruments	7488/188/288	X	32 x 8	256		OC	16	PROM
745188	Texas Instruments	7488/188/288	X	32 x 8	256		OC	16	PROM
745288	Texas Instruments	7488/188/288	X	32 x 8	256		OC	16	PROM
K155RE3	(UdSSR)	7488/188/288	X	32 x 8	256		TS	16	PROM
74185		7488/188/288	X	32 x 8	256		OC	16	ROM
74186		74186	(X)	64 x 8	512		OC	24	ROM
Vss = Pin 13 & Pin 23, untested									

Identifier	Company	Test setting	Pro Rev.1+	Organization	Size	TS/OC/AP	Pins	Type	Remark
74187		74187/287/387	X	256 x 4	1024	OC	16	ROM	
74287		74187/287/387	X	256 x 4	1024	TS	16	PROM	
74387		74187/287/387	X	256 x 4	1024	OC	16	PROM	
Am27510	AMD	74187/287/387	X	256 x 4	1024	OC	16	PROM	
Am27511	AMD	74187/287/387	X	256 x 4	1024	TS	16	PROM	
Am27520	AMD	74187/287/387	X	256 x 4	1024	OC	16	PROM	
Am27521	AMD	74187/287/387	X	256 x 4	1024	TS	16	PROM	
93406	Fairchild	74187/287/387	X	256 x 4	1024	OC	16	ROM	/CS1 and /CS2 (customer programmable)
93417	Fairchild	74187/287/387	X	256 x 4	1024	OC	16	PROM	
93427	Fairchild	74187/287/387	X	256 x 4	1024	TS	16	PROM	
93457	Fairchild	74187/287/387	X	256 x 4	1024	OC	16	PROM	
93467	Fairchild	74187/287/387	X	256 x 4	1024	TS	16	PROM	
MB7052	Fujitsu	74187/287/387	X	256 x 4	1024	TS	16	PROM	
MB7057	Fujitsu	74187/287/387	X	256 x 4	1024	OC	16	PROM	
H1024	Harris	74187/287/387	X	256 x 4	1024	OC	16	PROM	
HM7610	Harris	74187/287/387	X	256 x 4	1024	OC	16	PROM	
HM7611	Harris	74187/287/387	X	256 x 4	1024	TS	16	PROM	
3301A	Intel	74187/287/387	X	256 x 4	1024	OC	16	PROM	
3601	Intel	74187/287/387	X	256 x 4	1024	OC	16	PROM	
3621	Intel	74187/287/387	X	256 x 4	1024	TS	16	PROM	
IM5603	Intersil	74187/287/387	X	256 x 4	1024	OC	16	PROM	
IM5623	Intersil	74187/287/387	X	256 x 4	1024	TS	16	PROM	
M54700	Mitsubishi	74187/287/387	X	256 x 4	1024	OC	16	PROM	
5300	MMI	74187/287/387	X	256 x 4	1024	OC	16	PROM	
5301	MMI	74187/287/387	X	256 x 4	1024	TS	16	PROM	
6200	MMI	74187/287/387	X	256 x 4	1024	OC	16	PROM	
6201	MMI	74187/287/387	X	256 x 4	1024	TS	16	PROM	
6300	MMI	74187/287/387	X	256 x 4	1024	OC	16	PROM	
6301	MMI	74187/287/387	X	256 x 4	1024	TS	16	PROM	
635140	MMI	74187/287/387	X	256 x 4	1024	OC	16	PROM	
635141	MMI	74187/287/387	X	256 x 4	1024	TS	16	PROM	
5005	Motorola	74187/287/387	X	256 x 4	1024	OC	16	PROM	
uPD403	NEC	74187/287/387	X	256 x 4	1024	OC	16	PROM	
uPD423	NEC	74187/287/387	X	256 x 4	1024	TS	16	PROM	
82587	Signetics	74187/287/387	X	256 x 4	1024	TS	16	PROM	
825126	Signetics	74187/287/387	X	256 x 4	1024	OC	16	PROM	
825129	Signetics	74187/287/387	X	256 x 4	1024	TS	16	PROM	
825226	Signetics	74187/287/387	X	256 x 4	1024	OC	16	PROM	
825229	Signetics	74187/287/387	X	256 x 4	1024	TS	16	PROM	
24510	Texas Instruments	74187/287/387	X	256 x 4	1024	TS	16	PROM	
245A10	Texas Instruments	74187/287/387	X	256 x 4	1024	OC	16	PROM	
34510	Texas Instruments	74187/287/387	X	256 x 4	1024	TS	16	PROM	
TBP24510	Texas Instruments	74187/287/387	X	256 x 4	1024	TS	16	PROM	
TBP245A10	Texas Instruments	74187/287/387	X	256 x 4	1024	OC	16	PROM	
TBP34510	Texas Instruments	74187/287/387	X	256 x 4	1024	TS	16	PROM	
K556RT4	(UdSSR)	74187/287/387	X	256 x 4	1024	TS	16	PROM	
KR556RT4	(UdSSR)	74187/287/387	X	256 x 4	1024	TS	16	PROM	=3601
K155PE21/22/23/24	(UdSSR)	74187/287/387	X	256 x 4	1024		16	ROM	
745271		745271/470	X	256 x 8	2048	OC	20	ROM	
745371		745271/470	X	256 x 8	2048	TS	20	ROM	
745470		745271/470	X	256 x 8	2048	OC	20	PROM	
745471		745271/470	X	256 x 8	2048	TS	20	PROM	
Am27523	AMD	745271/470	X	256 x 8	2048	OC	20	PROM	
5308	MMI	745271/470	X	256 x 8	2048	OC	20	PROM	
5309	MMI	745271/470	X	256 x 8	2048	TS	20	PROM	
6308	MMI	745271/470	X	256 x 8	2048	OC	20	PROM	
6309	MMI	745271/470	X	256 x 8	2048	TS	20	PROM	
635280	MMI	745271/470	X	256 x 8	2048	OC	20	PROM	
635281	MMI	745271/470	X	256 x 8	2048	TS	20	PROM	
825135	Signetics	745271/470	X	256 x 8	2048	TS	20	PROM	
18522	Texas Instruments	745271/470	X	256 x 8	2048	TS	20	PROM	
28122	Texas Instruments	745271/470	X	256 x 8	2048	TS	20	PROM	
uPD421	NEC	745271/470	X	256 x 8	2048	TS	20	PROM	
745270		745270/570	X	512 x 4	2048	OC	16	ROM	
745370		745270/570	X	512 x 4	2048	TS	16	ROM	
745570		745270/570	X	512 x 4	2048	OC	16	PROM	
745571		745270/570	X	512 x 4	2048	TS	16	PROM	
Am27512	AMD	745270/570	X	512 x 4	2048	OC	16	PROM	
Am27513	AMD	745270/570	X	512 x 4	2048	TS	16	PROM	
93431	Fairchild	745270/570	X	512 x 4	2048	OC	16	PROM	
93436	Fairchild	745270/570	X	512 x 4	2048	OC	16	PROM	
93441	Fairchild	745270/570	X	512 x 4	2048	TS	16	PROM	
93446	Fairchild	745270/570	X	512 x 4	2048	TS	16	PROM	
MB7053	Fujitsu	745270/570	X	512 x 4	2048	OC	16	PROM	
HM7620	Harris	745270/570	X	512 x 4	2048	OC	16	PROM	
HM7621	Harris	745270/570	X	512 x 4	2048	TS	16	PROM	
3302	Intel	745270/570	X	512 x 4	2048	OC	16	PROM	
3322	Intel	745270/570	X	512 x 4	2048	TS	16	PROM	
3602	Intel	745270/570	X	512 x 4	2048	OC	16	PROM	
3622	Intel	745270/570	X	512 x 4	2048	TS	16	PROM	
IM5604	Intersil	745270/570	X	512 x 4	2048	OC	16	PROM	
IM5624	Intersil	745270/570	X	512 x 4	2048	TS	16	PROM	
5305	MMI	745270/570	X	512 x 4	2048	OC	16	PROM	
5306	MMI	745270/570	X	512 x 4	2048	TS	16	PROM	
6205	MMI	745270/570	X	512 x 4	2048	OC	16	PROM	
6206	MMI	745270/570	X	512 x 4	2048	TS	16	PROM	
6305	MMI	745270/570	X	512 x 4	2048	OC	16	PROM	
6306	MMI	745270/570	X	512 x 4	2048	TS	16	PROM	
635240	MMI	745270/570	X	512 x 4	2048	OC	16	PROM	
635241	MMI	745270/570	X	512 x 4	2048	TS	16	PROM	
MCM7620	Motorola	745270/570	X	512 x 4	2048	OC	16	PROM	
MCM7621	Motorola	745270/570	X	512 x 4	2048	TS	16	PROM	
29610	Raytheon	745270/570	X	512 x 4	2048	OC	16	PROM	
29611	Raytheon	745270/570	X	512 x 4	2048	TS	16	PROM	
825130	Signetics	745270/570	X	512 x 4	2048	OC	16	PROM	
825131	Signetics	745270/570	X	512 x 4	2048	TS	16	PROM	
825230	Signetics	745270/570	X	512 x 4	2048	OC	16	PROM	
825231	Signetics	745270/570	X	512 x 4	2048	TS	16	PROM	
745472		745472/473	X	512 x 8	4096	TS	20	PROM	
745473		745472/473	X	512 x 8	4096	OC	20	PROM	
Am27528	AMD	745472/473	X	512 x 8	4096	OC	20	PROM	
Am27529	AMD	745472/473	X	512 x 8	4096	TS	20	PROM	
93446	Fairchild	745472/473	X	512 x 8	4096	TS	20	PROM	
MB7123	Fujitsu	745472/473	X	512 x 8	4096	OC	20	PROM	
HM7648	Harris	745472/473	X	512 x 8	4096	OC	20	PROM	

Identifier	Company	Test setting	Pro Rev.1+	Organization	Size	TS/OC/AP	Pins	Type	Remark
HM7649	Harris	74S472/473	X	512 x 8	4096	TS	20	PROM	
D6304	Intel	74S472/473	X	512 x 8	4096	OC	20	PROM	
D6324	Intel	74S472/473	X	512 x 8	4096	TS	20	PROM	
M6304	Intel	74S472/473	X	512 x 8	4096	OC	20	PROM	
M6324	Intel	74S472/473	X	512 x 8	4096	TS	20	PROM	
5348	MMI	74S472/473	X	512 x 8	4096	OC	20	PROM	
5349	MMI	74S472/473	X	512 x 8	4096	TS	20	PROM	
6348	MMI	74S472/473	X	512 x 8	4096	OC	20	PROM	
6349	MMI	74S472/473	X	512 x 8	4096	TS	20	PROM	
63S480	MMI	74S472/473	X	512 x 8	4096	OC	20	PROM	
63S481	MMI	74S472/473	X	512 x 8	4096	TS	20	PROM	
uPD424	NEC	74S472/473	X	512 x 8	4096	TS	20	PROM	
29621	Raytheon	74S472/473	X	512 x 8	4096	TS	20	PROM	
82S146	Signetics	74S472/473	X	512 x 8	4096	OC	20	PROM	
82S147	Signetics	74S472/473	X	512 x 8	4096	TS	20	PROM	
18S42	Texas Instruments	74S472/473	X	512 x 8	4096	TS	20	PROM	
28L42	Texas Instruments	74S472/473	X	512 x 8	4096	TS	20	PROM	
28S42	Texas Instruments	74S472/473	X	512 x 8	4096	TS	20	PROM	
28SA42	Texas Instruments	74S472/473	X	512 x 8	4096	OC	20	PROM	
74S474		74S474/475	X	512 x 8	4096	TS	24	PROM	
74S475		74S474/475	X	512 x 8	4096	OC	24	PROM	untested, National Sem. datasheet claims different CS signals
Am27S30	AMD	74S474/475	X	512 x 8	4096	OC	24	PROM	untested
Am27S31	AMD	74S474/475	X	512 x 8	4096	TS	24	PROM	
93438	Fairchild	74S474/475	X	512 x 8	4096	OC	24	PROM	untested
93448	Fairchild	74S474/475	X	512 x 8	4096	TS	24	PROM	untested
MB7126	Fujitsu	74S474/475	X	512 x 8	4096	TS	24	PROM	untested
HM7640	Harris	74S474/475	X	512 x 8	4096	OC	24	PROM	untested, note: pin 22 is "internal connection" and should not be connected
HM7641	Harris	74S474/475	X	512 x 8	4096	TS	24	PROM	untested, note: pin 22 is "internal connection" and should not be connected
3304	Intel	74S474/475	X	512 x 8	4096	OC	24	PROM	untested
3324	Intel	74S474/475	X	512 x 8	4096	TS	24	PROM	untested
3604	Intel	74S474/475	X	512 x 8	4096	OC	24	PROM	untested
3624	Intel	74S474/475	X	512 x 8	4096	TS	24	PROM	untested
IM5605	Intersil	74S474/475	X	512 x 8	4096	OC	24	PROM	
IM5625	Intersil	74S474/475	X	512 x 8	4096	AP	24	PROM	
5340	MMI	74S474/475	X	512 x 8	4096	OC	24	PROM	untested
5341	MMI	74S474/475	X	512 x 8	4096	TS	24	PROM	untested
6340	MMI	74S474/475	X	512 x 8	4096	OC	24	PROM	untested
6341	MMI	74S474/475	X	512 x 8	4096	TS	24	PROM	untested
63S485	MMI	74S474/475	X	512 x 8	4096	TS	24	PROM	untested
MCM7640	Motorola	74S474/475	X	512 x 8	4096	OC	24	PROM	untested
MCM7641	Motorola	74S474/475	X	512 x 8	4096	TS	24	PROM	
87S295	National	74S474/475	X	512 x 8	4096	OC	24	PROM	untested
87S296	National	74S474/475	X	512 x 8	4096	TS	24	PROM	
uPB405	NEC	74S474/475	X	512 x 8	4096	OC	24	PROM	untested
uPB425	NEC	74S474/475	X	512 x 8	4096	TS	24	PROM	
29625	Raytheon	74S474/475	X	512 x 8	4096	TS	24	PROM	untested
82S140	Signetics	74S474/475	X	512 x 8	4096	OC	24	PROM	untested
82S141	Signetics	74S474/475	X	512 x 8	4096	TS	24	PROM	untested
28S46	Texas Instruments	74S474/475	X	512 x 8	4096	TS	24	PROM	untested
28SA46	Texas Instruments	74S474/475	X	512 x 8	4096	OC	24	PROM	untested
KR556RT5	(UdSSR)	74S474/475	X	512 x 8	4096		24	PROM	untested
74S476		74S476/572	X	1k x 4	4096	TS	18	PROM	
74S477		74S476/572	X	1k x 4	4096	OC	18	PROM	
74S572		74S476/572	X	1k x 4	4096	OC	18	PROM	
74S573		74S476/572	X	1k x 4	4096	TS	18	PROM	
Am27S32	AMD	74S476/572	X	1k x 4	4096	OC	18	PROM	
Am27S33	AMD	74S476/572	X	1k x 4	4096	TS	18	PROM	
93452	Fairchild	74S476/572	X	1k x 4	4096	OC	18	PROM	
93453	Fairchild	74S476/572	X	1k x 4	4096	TS	18	PROM	
MB7059	Fujitsu	74S476/572	X	1k x 4	4096	OC	18	PROM	
MB7121	Fujitsu	74S476/572	X	1k x 4	4096	OC	18	PROM	
MB7122	Fujitsu	74S476/572	X	1k x 4	4096	TS	18	PROM	
HM7642	Harris	74S476/572	X	1k x 4	4096	OC	18	PROM	
HM7643	Harris	74S476/572	X	1k x 4	4096	TS	18	PROM	
3605	Intel	74S476/572	X	1k x 4	4096	OC	18	PROM	
3625	Intel	74S476/572	X	1k x 4	4096	TS	18	PROM	
IM56506	Intersil	74S476/572	X	1k x 4	4096	OC	18	PROM	
IM56526	Intersil	74S476/572	X	1k x 4	4096	TS	18	PROM	
5352	MMI	74S476/572	X	1k x 4	4096	OC	18	PROM	
5353	MMI	74S476/572	X	1k x 4	4096	TS	18	PROM	
6352	MMI	74S476/572	X	1k x 4	4096	OC	18	PROM	
6353	MMI	74S476/572	X	1k x 4	4096	TS	18	PROM	
63S440	MMI	74S476/572	X	1k x 4	4096	OC	18	PROM	
63S441	MMI	74S476/572	X	1k x 4	4096	TS	18	PROM	
MCM7642	Motorola	74S476/572	X	1k x 4	4096	OC	18	PROM	
MCM7643	Motorola	74S476/572	X	1k x 4	4096	TS	18	PROM	
uPD406	NEC	74S476/572	X	1k x 4	4096	OC	18	PROM	
uPD426	NEC	74S476/572	X	1k x 4	4096	TS	18	PROM	
29641	Raytheon	74S476/572	X	1k x 4	4096	TS	18	PROM	
82S136	Signetics	74S476/572	X	1k x 4	4096	OC	18	PROM	
82S137	Signetics	74S476/572	X	1k x 4	4096	TS	18	PROM	
24S41	Texas Instruments	74S476/572	X	1k x 4	4096	TS	18	PROM	
24S441	Texas Instruments	74S476/572	X	1k x 4	4096	OC	18	PROM	
K556RT5	(UdSSR)	74S476/572	X	1k x 4	4096	OC	18	PROM	
74S450		74S478/74S479	X	1k x 8	8192	TS	24	PROM	untested
74S451		74S478/74S479	X	1k x 8	8192	OC	24	PROM	untested
74S478		74S478/74S479	X	1k x 8	8192	TS	24	PROM	untested
74S479		74S478/74S479	X	1k x 8	8192	OC	24	PROM	untested
Am27S80	AMD	74S478/74S479	X	1k x 8	8192	OC	24	PROM	untested
Am27S81	AMD	74S478/74S479	X	1k x 8	8192	TS	24	PROM	untested
Am27S180	AMD	74S478/74S479	X	1k x 8	8192	OC	24	PROM	untested
Am27S181	AMD	74S478/74S479	X	1k x 8	8192	TS	24	PROM	untested
CY7C281	Cypress	74S478/74S479	X	1k x 8	8192	TS	24	PROM	untested
CY7C282	Cypress	74S478/74S479	X	1k x 8	8192	TS	24	PROM	untested
93450	Fairchild	74S478/74S479	X	1k x 8	8192	OC	24	PROM	untested
93451	Fairchild	74S478/74S479	X	1k x 8	8192	TS	24	PROM	untested
93L450	Fairchild	74S478/74S479	X	1k x 8	8192	OC	24	PROM	untested
93L451	Fairchild	74S478/74S479	X	1k x 8	8192	TS	24	PROM	untested
MB7162	Fujitsu	74S478/74S479	X	1k x 8	8192	TS	24	PROM	untested
HM7680	Harris	74S478/74S479	X	1k x 8	8192	OC	24	PROM	untested, STROBE
HM7681	Harris	74S478/74S479	X	1k x 8	8192	TS	24	PROM	untested, STROBE
HN25089	Hitachi	74S478/74S479	X	1k x 8	8192	TS	24	PROM	untested
3608	Intel	74S478/74S479	X	1k x 8	8192	OC	24	PROM	untested
3628	Intel	74S478/74S479	X	1k x 8	8192	TS	24	PROM	untested
5380	MMI	74S478/74S479	X	1k x 8	8192	OC	24	PROM	untested

Identifier	Company	Test setting	Pro Rev.1+	Organization	Size	TS/OC/AP	Pins	Type	Remark
5381	MMI	745478/745479	X	1k x 8	8192	TS	24	PROM	untested
6380	MMI	745478/745479	X	1k x 8	8192	OC	24	PROM	untested
6381	MMI	745478/745479	X	1k x 8	8192	TS	24	PROM	untested
635880	MMI	745478/745479	X	1k x 8	8192	OC	24	PROM	untested
635881	MMI	745478/745479	X	1k x 8	8192	TS	24	PROM	untested
MCM7680	Motorola	745478/745479	X	1k x 8	8192	OC	24	PROM	untested
MCM7681	Motorola	745478/745479	X	1k x 8	8192	TS	24	PROM	untested
875180	National	745478/745479	X	1k x 8	8192	OC	24	PROM	untested
875181	National	745478/745479	X	1k x 8	8192	TS	24	PROM	untested
uPD408	NEC	745478/745479	X	1k x 8	8192	OC	24	PROM	untested
uPD428	NEC	745478/745479	X	1k x 8	8192	TS	24	PROM	untested
29631	Raytheon	745478/745479	X	1k x 8	8192	TS	24	PROM	untested
825180	Signetics	745478/745479	X	1k x 8	8192	OC	24	PROM	untested
825181	Signetics	745478/745479	X	1k x 8	8192	TS	24	PROM	untested
825183	Signetics	745478/745479	X	1k x 8	8192	TS	24	PROM	untested, STROBE
2607	Signetics	745478/745479	X	1k x 8	8192	TS	24	ROM	18=HIGH and 20=LOW
TBP28586	Texas Instruments	745478/745479	X	1k x 8	8192	TS	24	PROM	untested
TBP285A86	Texas Instruments	745478/745479	X	1k x 8	8192	OC	24	PROM	untested
7452708		2708	X	1k x 8	8192	TS	24	PROM	2708 replacement, Pin 18, 19, 21 not connected
7453708		2708	X	1k x 8	8192	OC	24	PROM	2708 replacement, Pin 18, 19, 21 not connected
93461C	Fairchild	2708	X	1k x 8	8192	TS	24	PROM	2708 replacement, Pin 18, 19, 21 not connected
HM7608	Harris	2708	X	1k x 8	8192	TS	24	PROM	2708 replacement, Pin 18, 19, 21 not connected
6384	MMI	2708	X	1k x 8	8192	OC	24	PROM	2708 replacement, Pin 18, 19, 21 not connected
6385	MMI	2708	X	1k x 8	8192	TS	24	PROM	2708 replacement, Pin 18, 19, 21 not connected
MCM82708	Motorola	2708	X	1k x 8	8192	TS	24	PROM	2708 replacement, Pin 18, 19, 21 not connected
uPB417	NEC	2708	X	1k x 8	8192	TS	24	PROM	2708 replacement, Pin 18, 19, 21 not connected
29635	Raytheon	2708	X	1k x 8	8192	TS	24	PROM	2708 replacement, Pin 18, 19, 21 not connected
8252708	Signetics	2708	X	1k x 8	8192	TS	24	PROM	2708 replacement, Pin 18, 19, 21 not connected
TBP2852708	Texas Instruments	2708	X	1k x 8	8192	TS	24	PROM	2708 replacement, Pin 18, 19, 21 not connected
275184	AMD	825184/825185	X	2k x 4	8192	OC	18	PROM	untested
275185	AMD	825184/825185	X	2k x 4	8192	TS	18	PROM	untested
93514	Fairchild	825184/825185	X	2k x 4	8192	OC	18	PROM	untested
93515	Fairchild	825184/825185	X	2k x 4	8192	TS	18	PROM	untested
MB7128	Fujitsu	825184/825185	X	2k x 4	8192	TS	18	PROM	untested
HM7684	Harris	825184/825185	X	2k x 4	8192	OC	18	PROM	untested
HM7685	Harris	825184/825185	X	2k x 4	8192	TS	18	PROM	untested
635840	MMI	825184/825185	X	2k x 4	8192	OC	18	PROM	untested
635841	MMI	825184/825185	X	2k x 4	8192	TS	18	PROM	untested
MCM7684	Motorola	825184/825185	X	2k x 4	8192	OC	18	PROM	untested
MCM7685	Motorola	825184/825185	X	2k x 4	8192	TS	18	PROM	untested
875184	National	825184/825185	X	2k x 4	8192	OC	18	PROM	untested
875185	National	825184/825185	X	2k x 4	8192	TS	18	PROM	untested
uPB427	NEC	825184/825185	X	2k x 4	8192	TS	18	PROM	untested
29651	Raytheon	825184/825185	X	2k x 4	8192	TS	18	PROM	untested
825184	Signetics	825184/825185	X	2k x 4	8192	OC	18	PROM	untested
825185	Signetics	825184/825185	X	2k x 4	8192	TS	18	PROM	untested
24581	Texas Instruments	825184/825185	X	2k x 4	8192	TS	18	PROM	untested
245A81	Texas Instruments	825184/825185	X	2k x 4	8192	OC	18	PROM	untested
275190	AMD	825190/825191	X	2k x 8	16384	OC	24	PROM	
275191	AMD	825190/825191	X	2k x 8	16384	TS	24	PROM	
27P5191	AMD	825190/825191	X	2k x 8	16384	TS	24	PROM	
CY7C291	Cypress	825190/825191	X	2k x 8	16384	TS	24	PROM	untested
CY7C292	Cypress	825190/825191	X	2k x 8	16384	TS	24	PROM	untested
CY7C293	Cypress	825190/825191	X	2k x 8	16384	TS	24	PROM	untested
XLS46C15	Exel	825190/825191	X	2k x 8	16384	TS	24	PROM	
93511P	Fairchild	825190/825191	X	2k x 8	16384	TS	24	PROM	untested
HM76160	Harris	825190/825191	X	2k x 8	16384	OC	24	PROM	
HM76161	Harris	825190/825191	X	2k x 8	16384	TS	24	PROM	
HN25168	Hitachi	825190/825191	X	2k x 8	16384	OC	24	PROM	untested
HN25169	Hitachi	825190/825191	X	2k x 8	16384	TS	24	PROM	untested
3606	Intel	825190/825191	X	2k x 8	16384	OC	24	PROM	untested
3636	Intel	825190/825191	X	2k x 8	16384	TS	24	PROM	untested
6351680	MMI	825190/825191	X	2k x 8	16384	OC	24	PROM	untested
6351681	MMI	825190/825191	X	2k x 8	16384	TS	24	PROM	untested
875191	National	825190/825191	X	2k x 8	16384	TS	24	PROM	
875191	National	825190/825191	X	2k x 8	16384	TS	24	PROM	
uPB409	NEC	825190/825191	X	2k x 8	16384	OC	24	PROM	
uPB429	NEC	825190/825191	X	2k x 8	16384	TS	24	PROM	
29681	Raytheon	825190/825191	X	2k x 8	16384	TS	24	PROM	untested
LH57191	Sharp	825190/825191	X	2k x 8	16384	OC	24	PROM	EPROM/OTEPROM, untested
825190	Signetics	825190/825191	X	2k x 8	16384	OC	24	PROM	
825191	Signetics	825190/825191	X	2k x 8	16384	TS	24	PROM	
285166	Texas Instruments	825190/825191	X	2k x 8	16384	TS	24	PROM	untested
285A166	Texas Instruments	825190/825191	X	2k x 8	16384	OC	24	PROM	untested
WS57C191	WSI	825190/825191	X	2k x 8	16384	OC	24	PROM	untested
WS57C291	WSI	825190/825191	X	2k x 8	16384	OC	24	PROM	untested
uPD419	NEC	2716	X	2k x 8	16384	TS	24	PROM	2716 replacement
27541	AMD	825195	X	4k x 4	16384	TS	20	PROM	untested
93513	Fairchild	825195	X	4k x 4	16384	TS	20	PROM	untested
HM76165	Harris	825195	X	4k x 4	16384	TS	20	PROM	untested
6351640	MMI	825195	X	4k x 4	16384	OC	20	PROM	untested
6351641	MMI	825195	X	4k x 4	16384	TS	20	PROM	untested
875195	National	825195	X	4k x 4	16384	TS	20	PROM	untested
825195	Signetics	825195	X	4k x 4	16384	TS	20	PROM	untested
27543	AMD	825321	X	4k x 8	32768	TS	24	PROM	untested
HM76321	Harris	825321	X	4k x 8	32768	TS	24	PROM	untested
3632	Intel	825321	X	4k x 8	32768	TS	24	PROM	untested
6353281	MMI	825321	X	4k x 8	32768	TS	24	PROM	untested
875321	National	825321	X	4k x 8	32768	TS	24	PROM	untested
29671	Raytheon	825321	X	4k x 8	32768	TS	24	PROM	untested
825321	Signetics	825321	X	4k x 8	32768	TS	24	PROM	untested
27549	AMD	825641	X	8k x 8	65536	TS	24	PROM	
AT27HC641	Atmel	825641	X	8k x 8	65536	TS	24	EPROM	EPROM/OTEPROM
CY7C261	Cypress	825641	X	8k x 8	65536	TS	24	EPROM	
CY7C262	Cypress	825641	X	8k x 8	65536	TS	24	EPROM	
CY7C263	Cypress	825641	X	8k x 8	65536	TS	24	EPROM	
932565	Fairchild	825641	X	8k x 8	65536	TS	24	PROM	
HM76641	Harris	825641	X	8k x 8	65536	TS	24	PROM	
M27HC641	Microchip	825641	X	8k x 8	65536	TS	24	PROM	
LH5749	Sharp	825641	X	8k x 8	65536	TS	24	EPROM	EPROM/OTEPROM
27HC641	Signetics	825641	X	8k x 8	65536	TS	24	ROM	
825641	Signetics	825641	X	8k x 8	65536	TS	24	PROM	
WS57C49	WSI	825641	X	8k x 8	65536	TS	24	PROM	
EEPROMs									
2804		2804	X	512 x 8	4096	TS	24	EEPROM	

Identifier	Company	Test setting	Pro Rev.1+	Organization	Size	TS/OC/AP	Pins	Type	Remark
AT28C04	Atmel	2804	X	512 x 8	4096	TS	24	EEPROM	
XL2804	Exel	2804	X	512 x 8	4096	TS	24	EEPROM	
28C04	GI	2804	X	512 x 8	4096	TS	24	EEPROM	
M28C04	Microchip	2804	X	512 x 8	4096	TS	24	EEPROM	
uPD28C04	NEC	2804	X	512 x 8	4096	TS	24	EEPROM	
2804A	Seeq	2804	X	512 x 8	4096	TS	24	EEPROM	
X2804	Xicor	2804	X	512 x 8	4096	TS	24	EEPROM	
AT28C16	Atmel	2716	X	2k x 8	16384		24	EEPROM	untested
CAT28C16	Catalyst	2716	X	2k x 8	16384		24	EEPROM	untested
ER5916	GI	2716	X	2k x 8	16384		24	EEPROM	untested
XL28C16	Exel	2716	X	2k x 8	16384		24	EEPROM	untested
2816	Intel	2716	X	2k x 8	16384		24	EEPROM	untested
HN48016	Hitachi	2716	X	2k x 8	16384		24	EEPROM	Vpp=25V, see manual
M28C16	Microchip	2716	X	2k x 8	16384		24	EEPROM	untested
CAT28C16	On Semiconductor	2716	X	2k x 8	16384		24	EEPROM	untested
KM2816	Samsung	2716	X	2k x 8	16384		24	EEPROM	untested
2816	Seeq	2716	X	2k x 8	16384		24	EEPROM	untested
5213	Seeq	2716	X	2k x 8	16384		24	EEPROM	untested
52813	Seeq	2716	X	2k x 8	16384		24	EEPROM	untested
5516	Seeq	2716	X	2k x 8	16384		24	EEPROM	untested
X2816	Xicor	2716	X	2k x 8	16384		24	EEPROM	untested
KP558PP	(UdSSR)	2716	X	2k x 8	16384		24	EEPROM	untested
2817A	Intel	custom	external	2k x 8	16384		28	EEPROM	untested
AT28C64	Atmel	2764	X	8k x 8	65536		28	EEPROM	
2864	Intel	2764	X	8k x 8	65536		28	EEPROM	
UPD28C64	NEC	2764	X	8k x 8	65536		28	EEPROM	
2864	Seeq	2764	X	8k x 8	65536		28	EEPROM	untested, do not connect pin 1 (RDY/BUSY)
AT28C256	Atmel	custom	external	32k x 8	262144	TS	28	EEPROM	different pinout, untested
AT29C256	Atmel	27256	X	32k x 8	262144		28	EEPROM	untested
AT29C512	Atmel	custom	external	64k x 8	524288		32	EEPROM	untested
28F512	Intel	custom	external	64k x 8	524288		32	EEPROM	untested
AT29C010	Atmel	custom	external	128k x 8	1048576		32	EEPROM	untested
28F010	Intel	custom	external	128k x 8	1048576		32	EEPROM	untested
W29F011	Winbond	custom	external	128k x 8	1048576		32	EEPROM	untested
28F020	Intel	custom	external	256k x 8	2097152		32	EEPROM	untested
Am29F002	AMD	custom	external	256k x 8	2097152		32	EEPROM	untested
SST29EE020	SST	custom	external	256k x 8	2097152		32	EEPROM	untested
PLAS									
906114-01	CBM	custom	external	I/O: 16/8		TS	28	825100	C64 PLA, external definition available (825100 or PLA2EPROM)
251641-02	CBM	custom	external	I/O: 16/8		TS	28	825100	C116/Plus4 PLA, external definition available (825100 or PLA2EPROM)
251641-03	CBM	custom	external	I/O: 16/8		TS	28	825100	1551 PLA, external definition available (825100 or PLA2EPROM)
Cartridges & Cartridge ROMs									
VCS/2600 (2k Cart)	Atari	VCS/2600 Cart	adapter	2k x 8	16384		Cart	ROM	Atari VCS/2600 Cartridge, 2k Byte, adapter required
VCS/2600 (4k Cart)	Atari	VCS/2600 Cart	adapter	4k x 8	32768		Cart	ROM	Atari VCS/2600 Cartridge, 4k Byte, adapter required
VCS/2600 (8k Cart)	Atari	VCS/2600 Cart	adapter	8k x 8	65536		Cart	ROM	Atari VCS/2600 Cartridge, 8k Byte bank-switched, adapter required
VCS/2600 (8k ROM)	Atari	custom	X	8k x 8	65536		24	ROM	Atari VCS/2600 Cartridge, 8k Byte bank-switched, external definition available
VCS/2600 (16k Cart)	Atari	VCS/2600 Cart	adapter	16k x 8	131072		Cart	ROM	Atari VCS/2600 Cartridge, 16k Byte bank-switched, adapter required
C64 (16k Cart)	Commodore	2764	adapter	2x 8k x 8	131072		Cart	ROM	Commodore 64 Cartridge, select HIGH or LOW, adapter required
VC20 (BLK1, Cart)	Commodore	2764	adapter	8kx 8	65536		Cart	ROM	Commodore VC20 Cartridge, BLK1, adapter required
VC20 (BLK2, Cart)	Commodore	2764	adapter	8kx 8	65536		Cart	ROM	Commodore VC20 Cartridge, BLK2, adapter required
VC20 (BLK3, Cart)	Commodore	2764	adapter	8kx 8	65536		Cart	ROM	Commodore VC20 Cartridge, BLK3, adapter required
VC20 (BLK5, Cart)	Commodore	2764	adapter	8kx 8	65536		Cart	ROM	Commodore VC20 Cartridge, BLK5, adapter required
other ICs supported with external definitions									
MCM5003	Motorola	custom	external	64 x 8	512	OC	24	PROM	untested
MCM5004	Motorola	custom	external	64 x 8	512	OC	24	PROM	internal 2k pullup, untested
MCM5303	Motorola	custom	external	64 x 8	512	OC	24	PROM	untested
MCM5304	Motorola	custom	external	64 x 8	512	OC	24	PROM	internal 2k pullup, untested
MCM14524	Motorola	custom	external	256 x 4	1024	TS	16	ROM	clocked, untested
825114	Signetics	custom	external	256 x 8	2048	TS	24	PROM	latched, Pin 3=nc, Pin 11, 13 = FE (fusing pins = low or floating), untested
825214	Signetics	custom	external	256 x 8	2048	TS	24	PROM	latched, Pin 3=nc, Pin 11, 13 = nc
8204	Signetics	custom	external	256 x 8	2048	TS	24	PROM	latched, Pin 3=nc, Pin 11, 13 = nc
825115	Signetics	custom	external	512 x 8	4096	TS	24	PROM	latched, Pin 11, 13 = FE (fusing pins = low or floating), untested
825215	Signetics	custom	external	512 x 8	4096	TS	24	PROM	latched, Pin 11, 13 = nc
8205	Signetics	custom	external	512 x 8	4096	TS	24	PROM	latched, Pin 11, 13 = nc
27515	AMD	custom	external	512 x 8	4096	TS	24	PROM	latched, Pin 11, 13 not connected, LO = Output Latch Enable, untested
5335	MMI	custom	external	256 x 8	2048	OC	18	PROM	use MMI6335
5336	MMI	custom	external	256 x 8	2048	TS	18	PROM	use MMI6336
5350	MMI	custom	external	1024 x 4	4096	OC	18	PROM	use MMI6350
5351	MMI	custom	external	1024 x 4	4096	TS	18	PROM	use MMI6351
5386	MMI	custom	external	1024 x 8	8192	OC	18	PROM	use MMI6386
5387	MMI	custom	external	1024 x 8	8192	TS	18	PROM	use MMI6387
6335	MMI	custom	external	256 x 8	2048	OC	18	PROM	
6336	MMI	custom	external	256 x 8	2048	TS	18	PROM	
6350	MMI	custom	external	1024 x 4	4096	OC	18	PROM	
6351	MMI	custom	external	1024 x 4	4096	TS	18	PROM	
6386	MMI	custom	external	1024 x 8	8192	OC	18	PROM	
6387	MMI	custom	external	1024 x 8	8192	TS	18	PROM	
2600	Signetics	custom	external	2048 x 8	16384	TS	24	ROM	1=Vss, 9=Vcc, 13=AR, similar TMS4800 but different voltages
2608	Signetics	custom	external	1024 x 8	8192	TS	24	ROM	1=Vss, 12=Vcc, 4xCS, not compatible to Intel 2608, untested
56830	Ami	custom	external	1024 x 8	8192	TS	24	ROM	1=Vss, 12=Vcc, 4xCS, not compatible to Intel 2608, untested
MCM68A30	Motorola	custom	external	1024 x 8	8192	TS	24	ROM	1=Vss, 12=Vcc, 4xCS, not compatible to Intel 2608, untested
MCM68B30	Motorola	custom	external	1024 x 8	8192	TS	24	ROM	1=Vss, 12=Vcc, 4xCS, not compatible to Intel 2608, untested
MCM68A308	Motorola	custom	external	1024 x 8	8192	TS	24	ROM	untested
MCM68B308	Motorola	custom	external	1024 x 8	8192	TS	24	ROM	untested
2617	Signetics	custom	external	2048 x 8	16384	TS	24	ROM	12=Vss, 24=Vcc, 21=A10, , similar Am9216 but single 5V, untested
CDP1831	RCA	custom	external	512 x 8	4096	TS	24	ROM	requires 64k address, 512 byte segment start is hardcoded
CDP1833	RCA	custom	external	1024 x 8	8192	TS	24	ROM	requires 64k address, 1024 byte segment start is hardcoded
HM7644	Harris	custom	external	1024 x 4	4096	AP	16	ROM	untested
74262		custom	external	128 x 9 x 5	5760	TS	20	ROM	ROM, TIFAX/Videodat, untested
745262		custom	external	128 x 9 x 5	5760	TS	20	ROM	ROM, TIFAX/Videodat, untested
Am9216	AMD	custom	external	2048 x 8	16384	TS	24	ROM	ROM, 19=Vdd(12V), similar Signetics 2617 but Vdd, untested
LH534	Sharp	custom	external	512k x 8	524288	TS	32	ROM	
LH538	Sharp	custom	external	1024k x 8	1048576	TS	32	ROM	
IM6654	Intersil	custom	external	512 x 8	4096	TS	24	EPROM	untested
IM6653	Intersil	custom	external	1024 x 4	4096	TS	24	EPROM	untested
IM6658	Intersil	custom	external	1024 x 8	8192	TS	24	EPROM	untested
IM6657	Intersil	custom	external	2048 x 4	8192	TS	24	EPROM	untested
M48T08_Dumping	ST Microelectronics	custom	external	8k x 8	65536	TS	24	TK-SRAM	Timekeeper SRAM, used for dumping, untested
M48T18_Dumping	ST Microelectronics	custom	external	8k x 8	65536	TS	24	TK-SRAM	Timekeeper SRAM, used for dumping, untested
M48T58_Dumping	ST Microelectronics	custom	external	8k x 8	65536	TS	24	TK-SRAM	Timekeeper SRAM, used for dumping, untested
M48Z08_Dumping	ST Microelectronics	custom	external	8k x 8	65536	TS	24	ZP-SRAM	Zeropower SRAM, used for dumping, untested
M48Z18_Dumping	ST Microelectronics	custom	external	8k x 8	65536	TS	24	ZP-SRAM	Zeropower SRAM, used for dumping, untested
M48Z58_Dumping	ST Microelectronics	custom	external	8k x 8	65536	TS	24	ZP-SRAM	Zeropower SRAM, used for dumping, untested
M48T35_Dumping	ST Microelectronics	custom	external	32k x 8	65536	TS	24	TK-SRAM	Timekeeper SRAM, used for dumping
M48Z35_Dumping	ST Microelectronics	custom	external	32k x 8	65536	TS	24	ZP-SRAM	Zeropower SRAM, used for dumping

Identifier	Company	Test setting	Pro Rev.1+	Organization	Size	TS/OC/AP	Pins	Type	Remark
TMS2508	Texas Instruments	custom	external	1024 x 8	8192	TS	24	EPROM	single 5V, 20=/CS, 19=nc, untested
HM6758	Harris	custom	external	1024 x 8	8192	TS	24	EPROM	single 5V, 20=/CS, 19=AR (0 = L, 1 = -H), untested
2758	Intel	custom	external	1024 x 8	8192	TS	24	EPROM	single 5V, 20=/CS, 19=AR (0 = L, 1 = S1865), untested
MM2758	National	custom	external	1024 x 8	8192	TS	24	EPROM	single 5V, 20=/CS, 19=AR, untested
MSM2758	Oki	custom	external	1024 x 8	8192	TS	24	EPROM	single 5V, 20=/CS, 19=AR, untested
TMS2758	Texas Instruments	custom	external	1024 x 8	8192	TS	24	EPROM	single 5V, 20=/CS, 19=AR (0 = -J10, 1 = -J11), untested
external definition and adapter required									
uPD454	NEC	custom	adapter	256 x 8	2048	TS	24	EEPROM	external definition and adapter required
uPD464	NEC	custom	adapter	256 x 8	2048	TS	24	ROM	external definition and adapter required
2530	Signetics	custom	adapter	512 x 8	4096	TS	24	ROM	4=GND, 12=-12V, 24=Vcc, adapter required
EA4800	EA	custom	adapter	2k x 8	16384	OC	24	ROM	1=5V, 9=-12V, 24/14=OE, similar Signetics 2600 but diff. voltages, MK28000 adapte
EA4900	EA	custom	adapter	2k x 8	16384	OC	24	ROM	1=5V, 9=-12V, 24/14=OE, similar Signetics 2600 but diff. voltages, MK28000 adapte
MK28000	Mostek	custom	adapter	2k x 8	16384	OC	24	ROM	1=5V, 9=-12V, 24/14=OE, similar Signetics 2600 but diff. voltages, MK28000 adapte
TMS4800	Texas Instruments	custom	adapter	2k x 8	16384	OC	24	ROM	1=5V, 9=-12V, 24/14=OE, similar Signetics 2600 but diff. voltages, MK28000 adapte
MX27C1100	MXIC	custom	adapter	128k x 8	1 MBit	TS	40	EPROM	128k x 8 / 64k x 16, external definition and adapter required, untested
MX23C2100	MXIC	custom	adapter	256k x 8	2 MBit	TS	40	ROM	256k x 8 / 128k x 16, external definition and adapter required, untested
MX27C2100	MXIC	custom	adapter	256k x 8	2 MBit	TS	40	EPROM	256k x 8 / 128k x 16, external definition and adapter required, untested
uPD23C2000	NEC	custom	adapter	256k x 8	2 MBit	TS	40	ROM	256k x 8 / 128k x 16, external definition and adapter required, untested
AT27C400	Atmel	custom	adapter	512k x 8	4 MBit	TS	40	EPROM	512k x 8 / 256k x 16, external definition and adapter required, untested
HN27C4000	Hitachi	custom	adapter	512k x 8	4 MBit	TS	40	EPROM	512k x 8 / 256k x 16, external definition and adapter required, untested
MX27C4100	MXIC	custom	adapter	512k x 8	4 MBit	TS	40	EPROM	512k x 8 / 256k x 16, external definition and adapter required, untested
uPD23C4000	NEC	custom	adapter	512k x 8	4 MBit	TS	40	ROM	512k x 8 / 256k x 16, external definition and adapter required, untested
M27C400	ST Microelectronics	custom	adapter	512k x 8	4 MBit	TS	40	EPROM	512k x 8 / 256k x 16, external definition and adapter required, untested
TC534200	Toshiba	custom	adapter	512k x 8	4 MBit	TS	40	ROM	512k x 8 / 256k x 16, external definition and adapter required, untested
AT27C8192	Atmel	custom	adapter	1024k x 8	8 MBit	TS	42	EPROM	1024k x 8 / 512k x 16, external definition and adapter required, untested
KM23C8105	Samsung	custom	adapter	1024k x 8	8 MBit	TS	42	ROM	1024k x 8 / 512k x 16, external definition and adapter required, untested
M27C800	ST Microelectronics	custom	adapter	1024k x 8	8 MBit	TS	42	EPROM	1024k x 8 / 512k x 16, external definition and adapter required, untested
TC538200	Toshiba	custom	adapter	1024k x 8	8 MBit	TS	42	ROM	1024k x 8 / 512k x 16, external definition and adapter required, untested
KM23C16000	Samsung	custom	adapter	2048k x 8	16 MBit	TS	42	ROM	2048k x 8 / 1024k x 16, external definition and adapter required, untested
M27C160	ST Microelectronics	custom	adapter	2048k x 8	16 MBit	TS	42	EPROM	2048k x 8 / 1024k x 16, external definition and adapter required, untested
TC5316200	Toshiba	custom	adapter	2048k x 8	16 MBit	TS	42	ROM	2048k x 8 / 1024k x 16, external definition and adapter required, untested
currently unsupported									
Ro-3-5120	GI	-		512 x 10	5120	TS	24	ROM	ROM
Ro-3-9502	GI	-		2k x 10	20480	TS	40	ROM	ROM, 16 Bit Bus, address/data multiplexed
Ro-3-9504	GI	-		2k x 10	20480	TS	28	ROM	ROM, 16 Bit Bus, address/data multiplexed
Ro9580	GI	-		8k x 10	81920	TS	28	ROM	ROM, 16 Bit Bus, address/data multiplexed
Ro9160	GI	-		16k x 10	163840	TS	28	ROM	ROM, 16 Bit Bus, address/data multiplexed
Ro9508	GI	-		4k x 10	40960	TS	28	ROM	ROM, 16 Bit Bus, address/data multiplexed
8702	Intel	-		256 x 8	2048	TS	24	PROM	12/22/23=Vcc(5V), 15=Vbb(-5V), 16=Vgg(-9V), 25=Vdd(-9V)
2580	Signetics	-		2048 x 4	8192	TS	24	ROM	1=Vcc, 2=GND, 24=0V, 15=-12V
2609	Signetics	-		128 x 7 x 9	8192	TS	24	ChrROM	2=Vcc, 13=Vss
MCM6570	Motorola	-		128 x 7 x 9	8192	TS	24	ChrROM	2=Vcc, 13=Vss, 3=Vdd, 1=Vbb(-3v)
MCM66700	Motorola	-		128 x 7 x 9	8192	TS	24	ChrROM	also MCM66710, 14, 20, 30, 34, 40, 50, 51, 60, 70, 80, 90
HM7647	Harris	-		512 x 8	4096	TS	24	PROM	latched
ER2055	GI	-		64 x 8	512	TS	22	EAPROM	Vgg=-28V, Vss=5V
MM4203	National	-		256x8/512x4	2048	TS	24	EPROM	15=mode control, Vll=Vdd=-12V
MM5203	National	-		256x8/512x4	2048	TS	24	EPROM	15=mode control, Vll=Vdd=-12V
MM5213	National	-		256x8/512x4	2048	TS	24	ROM	ROM, 15=Mode Control, Vll=Vdd=-12V
56834	AMI	-		512 x 8	4096	TS	24	EPROM	1=Vss, 10=Vgg, 11=Vprog, 12/13=Vcc

green = implemented in Chip Tester
yellow = untested
red = not yet implemented or not possible to implement
(X) = could not be tested with working sample yet